

Ribbon Star Extreme Outdoor LED Strip Light - 24VDC


SKU: RL-SC-RSX

ECOLOCITY
LED LIGHTING SOLUTIONS

1092 Greg Street
Sparks, NV 89431
ECOLOCITYLED.COM
775-636-6060



SPECIFICATIONS



Product SKU : RL-SC-RSX
LED Size : 3528 SMD
LED Quantity : 7 LEDs per 6.50"
Input Power : 24VDC Constant Voltage
Watts : 0.96W per foot
Max Serial Connection : 100ft
Operating Temp : -4° ~ 104°F
Beam Angle : 120°
Rating : IP67
Warranty Period : 2 Years

Input Power: 24VDC Constant Voltage

Power supply equation

$$X * 0.96 = Y$$

X = linear strip light footage

Y = minimum transformer wattage

PRECAUTIONS



WARNING - This product should be installed, cut and connected only by a qualified professional.



NEVER cut, connect, or join wires while product is connected to a live power source.



24VDC Use 24VDC Input Only!



DO NOT bend or crease the strip in a manner that will damage the conductivity of the circuit board.



DO NOT use AC Input!



To extend the life of this product do not use in direct sun or environments over 104°F.



This product must be sealed properly with glue and end caps after cutting to retain IP67 waterproof rating.



DO NOT exceed 100ft serial connection!
BE CERTAIN your 24VDC source and wire gauge is suffice for powered load.

1092 Greg Street
Sparks, NV 89431, USA

ECOLOCITY
LED LIGHTING SOLUTIONS

ECOLOCITYLED.COM
775-636-6060

Ribbon Star Extreme Outdoor LED Strip Light - 24VDC

SKU: RL-SC-RSX

INSTALLATION


REQUIRED SUPPLIES



Cleaning Supplies
or Degreaser



Stranded Wire and
Wire Strippers



Wire Nuts or
Connectors




12VDC Power
Supply

OPTIONAL SUPPLIES




AND




End Caps, adhesive, Solder Iron and Heat Shrink
(Required to cut and re-connect)

1.) Clean Mounting Surface




Use your cleaning supplies to clean your mounting surface. Please note that mounting surface must be smooth, clean and dry for the 3M tape to permanently adhere.

2.) Connect Transformer



WARNING – This step should be done by a qualified professional. Always disable AC power before connecting! Use wire nuts or connectors to secure your AC input to your 24V transformer.

3.) Connect Strip Lights



Always be certain power is disabled before connecting! Use wire nuts, connectors, or solder and heat shrink to secure your 24V DC+ and DC- output wires to your LED Strip Light.




4.) Test and Mount Strip Lights



Use your cleaning supplies to clean your mounting surface. Please note that mounting surface must be smooth, clean and dry for the 3M tape to permanently adhere.

CONNECTION EXAMPLES: 0.96 Watts per foot




POWER SUPPLY AND CONTROLLER AMP OUTPUT RATING MUST BE GREATER THAN THE LOAD OF THE STRIP LIGHT OUTPUT.




SKU: RL-SC-RSX

SOLDERING INSTRUCTION

REQUIRED SUPPLIES

Rosin Core
Electrical SolderElectrical Soldering Iron
(Preferably Temp Adjustable)Stranded Wire and
Wire StrippersRazor Blade or
Cutting ToolSilicone
AdhesiveStrip Light
End CapsMasking
Tape

1.) Cut Waterproof Coating



Cut your strip light to length on the cut line only. Then use a sharp blade or cutting tool to expose the copper pads enough for soldering.

2.) Tin Strip Light Pads




Heat your soldering iron to 500-600°F. Use a piece of masking tape to secure your strip then tin each copper pad with rosin core electrical solder.

3.) Strip and Tin Wire




Strip your 2 conductor stranded wire roughly 1/8". Tin the exposed wires with rosin core solder.

4.) Push Wires through Cap




Push your connection wires through the plastic end cap with wire holes. Be sure to face the end cap in the right direction.

5.) Solder Wire to Strip




Mate your tinned wire to the copper pad with respective polarity. Red wire to DC+ (positive), Black wire to DC- (negative).

6.) Test Connection




Before permanently adhering your end cap to the strip light, it is a good idea to test your connection first.

7.) Glue End Cap



You can now glue on your end cap. We recommend using RTV 4500 Silicone adhesive, fill the entire end cap and gum all commisures.

8.) Let Glue Set



Our waterproof strip lights have a hollow inside. Be certain to hang the strip vertical so that the glue sets inside the mounting cap.

STRIP LIGHT ACCESSORIES:

Waterproof Strip
Light Connectors

24VDC Power Supplies



PWM LED Dimmers

Aluminium Extrusions
and Covers

HELPFUL LINKS:

24VDC Power Supplies - https://www.ecolocityled.com/category/led_power_supplies_24v

PWM LED Dimmers - https://www.ecolocityled.com/category/pwm_led_light_dimmer

18AWG Connection Wire - https://www.ecolocityled.com/product/50ft_dc_connection_wire_bonded

Aluminium Extrusions - https://www.ecolocityled.com/category/led_aluminum_extrusions

Strip Light Soldering Guide - https://www.ecolocityled.com/category/led_tutorials_dc_solder