



PRODUCT NAME	24 Channel LED DMX Driver, 5-24VDC 3A/CH
SKU	LC-EU-DMX-PX243
URL	Click Here
DESCRIPTION	This DMX512 driver allows for 24 Channels of LED lights to be controlled via a DMX controller by accepting both DC supply voltage and your DMX controller signal and distributing it to attached LED lights. This driver accepts either XLR-3 type connections or bare wire connections for the DMX signal input and output. There are a total of eight, 3 channel, common anode outputs with screw-down terminal blocks for easy connection to your LED lights. This driver is able to accept 5-24VDC at 3A per channel (twenty four channels total). You can set the starting address of the DMX driver via DIP switches located on the back of the unit. Please note that each DMX driver requires 24 addresses in the DMX universe being used.
CONTROLLER TYPE	DMX512
SUPPLY VOLTAGE	5VDC, 12VDC or 24VDC constant voltage
OUTPUT	24 channels
DIMMING	256 shades of grayscale per channel
CONNECTION TYPE	4 pin, 3 loop, common anode
DIMENSIONS	10.24"L x 4.72"W x 1.57"H (260mm x 120mm x 40mm)
OUTPUT CURRENT	3A per channel x 24 channels
OUTPUT POWER	360W/5VDC, 864W/12VDC , 1728W/24VDC maximum
WARRANTY	1 year manufacturers

These specification are subject to change without notice. This specification information is from the manufacturer of this product. Ecolocity LED is not the manufacturer of this product.
Copyright © 2014 Ecolocity LED