


## SPECIFICATIONS

## LED Dimmer with Key Fob Remote, 12-24VDC 30A




Frequency	Curve
1	1
2	2
3	3
4	4
5	5

### DIP Switch Settings

1	2	3	PWM	AMPS
↑	↑	↑	300HZ	30A
↓	↑	↑	500HZ	30A
↑	↓	↑	700HZ	30A
↓	↓	↑	1KHZ	30A
↑	↑	↓	3KHZ	20A
↓	↑	↓	5KHZ	15A
↑	↓	↓	10KHZ	10A

4	5	Curve
↑	↑	1
↓	↑	2
↑	↓	3



<b>PRODUCT NAME</b>	Frequency Adjustable LED Dimmer with Key Fob RF Remote, 12-24V 30A
<b>SKU</b>	LC-LF-1DIM
<b>PRODUCT URL</b>	<a href="#">Click Here</a>
<b>DESCRIPTION</b>	Our small sized flicker free LED dimmer uses a uniquely paired key fob RF remote to dim and control your 12-24VDC constant voltage LED lights and dip switches to adjust the PWM frequency and dimming curve. The impressive 30 amp output allows for dimming control of larger circuits without the need of additional accessories, when set to higher PWM frequencies the maximum load decreases. Choose from 5-100% range of dimming levels using two simple arrow buttons on the remote. Our key fob led dimmer can be used to dim LED strip lights, LED modules, LED wall washers, or for dimming any one color common anode 12VDC or 24VDC LED products.
<b>CONTROLLER TYPE</b>	PWM
<b>SUPPLY VOLTAGE</b>	12-24VDC constant voltage
<b>OUTPUT</b>	1 channel
<b>DIMMING</b>	0 to 100%
<b>CONNECTION TYPE</b>	2 Wire (+/-), common anode
<b>DIMENSIONS</b>	3.35" x 2.44" x 1.38"H
<b>OUTPUT CURRENT</b>	10A - 30A per channel (1 channel)
<b>OUTPUT POWER</b>	12VDC: 120W - 360W   24VDC: 240W - 720W
<b>WARRANTY</b>	1 year manufacturers

These specification are subject to change without notice. This specification information is from the manufacturer of this product. Ecolocity LED is not the manufacturer of this product.  
Copyright © 2023 Ecolocity LED