

# M-SERIES 12V

## DIMMER COMPATIBILITY LIST

### About Dimmer Compatibility

The dimmers listed below were tested with the specified Magnitude LED drivers. We are constantly adding to our list of compatible dimmers.

This chart describes the lowest measured electrical output when using the dimmer/driver combination. Some dimmers have wider dimming range. Zero (0%) means dim to off. One percent (1%) and five percent (5%) provide good dimming range. However, these percentages do not accurately describe the perception of the lamp, which is subjective to the individual viewer.

This compatibility list also takes into account other quality considerations such as flicker or pulsation. We do not recommend dimmers with these issues. In those cases where a dimmer is not compatible, we have suggested an alternate Magnitude product.

	Minimum Dimming Percentage			
DIMMER TYPE	PS-MT-60-12	PS-MT-150-12	PS-MT-200-12	PS-MT-300-12
<b>Lutron Caseta, Wireless</b> PD-6WCL (MLV)	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%
<b>Lutron Maestro, Wireless</b> MRF2-6CL (MLV)	Approved	Not Recommended	Approved	Approved
<b>Legrand Adorne</b> ADWR700MMTU (MLV)	Not Recommended	Not Recommended	Approved	Approved
<b>Lutron Radio RA 2</b> RRD-6ND (MLV)	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%
<b>Lutron Maestro</b> MA-600 (MLV)	Recommend Magnitude's E-Series Driver	Not Recommended	Not Recommended	Not Recommended
<b>Legrand Adorne</b> ADTP703TUW4 (MLV)	Approved	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%
<b>Leviton Decore Smart</b> DW6HD (MLV)	Approved Dims to 0%	Approved Dims to 0%	Approved Dims to 0%	Approved Dims to 0%
<b>Lutron Nova T</b> NTLV-600 (MLV)	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%
Note: M-Series supports MLV (Forward-Phase) dimming only.				

# M-SERIES 12V

## DIMMER COMPATIBILITY LIST

	Minimum Dimming Percentage			
DIMMER TYPE	PS-MT-60-12	PS-MT-150-12	PS-MT-200-12	PS-MT-300-12
<b>Leviton illumatech</b> IPMO6 (MLV)	Recommend Magnitude's E-Series Driver	Not Recommended	Not Recommended	Not Recommended
<b>Lutron Ariadni</b> AYLV-600P (MLV)	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%
<b>Lutron Diva</b> DVLV-600P (MLV)	Approved Dims to 1%	Not Recommended	Not Recommended	Not Recommended
<b>Lutron Caseta, Wireless</b> PD-10NXD (MLV)	Approved	Approved	Approved	Approved
<b>Lutron Diva</b> DVCL-153P (MLV)	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%
<b>Lutron Maestro</b> MA-PRO (MLV/ELV) MLV Result	Approved	Approved	Approved	Approved
<b>Lutron Radio RA2</b> RRD-PRO (MLV/ELV) MLV Result	Approved	Approved	Approved	Approved
<b>Lutron Caseta, Wireless</b> PD-5NE (MLV/ELV) MLV Result	Approved	Approved	Approved	Approved
<b>LeGrand Tru-Universa</b> RH703PTUW (MLV Mode)	Approved	Not Recommended	Approved	Approved
<b>LeGrand Adorne</b> AADTP700RMTUM1 (MLV)	Approved	Not Recommended	Approved	Approved
<b>Lutron Maestro+ Motion Sensor</b> MSCL-OP153MH	Approved Dims to 0%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%
<b>Lutron Caseta Smart Home Plug-in</b> PD-3PCL	Approved	Approved	Approved	Approved
Note: M-Series supports MLV (Forward-Phase) dimming only.				

# M-SERIES 12V

## DIMMER COMPATIBILITY LIST

	Minimum Dimming Percentage			
DIMMER TYPE	PS-MT-60-12	PS-MT-150-12	PS-MT-200-12	PS-MT-300-12
<b>Lutron Maestro</b> MACL-153P	Approved Dims to 0%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%
<b>Lutron Maestro IR</b> MIRLV-600P	Not Recommended	Not Recommended	Not Recommended	Not Recommended
<b>Lutron Maestro</b> MSC-1000M	Not Recommended	Not Recommended	Not Recommended	Not Recommended
<b>Lutron Toggle</b> TGCL-153P	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 0%	Approved Dims to 0%
<b>Lutron Sunnata Touch</b> STCL-153P	Approved Dims to 1%	Approved Dims to 0%	Approved Dims to 1%	Approved Dims to 1%
<b>Leviton Sureslide</b> 6674	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%
<b>Leviton Toggle Slide</b> TSM10-1LI	Not Recommended	Not Recommended	Approved Dims to 1%	Approved Dims to 1%
<b>leviton Decora Smart</b> DW1KD-1BZ	Approved Dims to 0%	Approved Dims to 0%	Approved Dims to 0%	Approved Dims to 0%
<b>leviton Decora Digital</b> DDMX1-BLZ	Approved	Approved	Approved	Approved
<b>leviton Decora Digital</b> DDL06-1LZ	Not Recommended	Not Recommended	Not Recommended	Not Recommended
<b>leviton Decora Slide</b> DSM10	Approved Dims to 1%	Not Recommended	Approved Dims to 1%	Approved Dims to 1%
<b>leviton Decora Slide</b> DSL06-1LZ	Approved Dims to 1%	Approved Dims to 1%	Not Recommended	Not Recommended
<b>GE Z-wave plus</b> ZW3005	Approved Dims to 0%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%
<b>HALO Smart</b> HIWAC1BLE40AWH	Not Recommended	Not Recommended	Not Recommended	Not Recommended
Note: M-Series supports MLV (Forward-Phase) dimming only.				

# M-SERIES 12V

## DIMMER COMPATIBILITY LIST

	<b>Minimum Dimming Percentage</b>			
<b>DIMMER TYPE</b>	<b>PS-MT-60-12</b>	<b>PS-MT-150-12</b>	<b>PS-MT-200-12</b>	<b>PS-MT-300-12</b>
<b>WeMo WiFi</b> F7C059	Approved	Approved	Approved	Approved
<b>Insteon Smart</b> 2477DH	Not Recommended	Not Recommended	Not Recommended	Not Recommended
<b>TP-Link Kasa Smart</b> HS220P3	Approved Dims to 0%	Approved Dims to 1%	Approved Dims to 1%	Approved Dims to 1%
Note: M-Series supports MLV (Forward-Phase) dimming only.				